

Luma

Model: 551-3

Watts: 900

Heat Stages: 3



Output Voltages

<u>AB/Low</u>	<u>BC/Med</u>	<u>AC/High</u>
1.7	2.9	4.6

1. Choose one of three secondary circuits: AB/Low, BC/Medium, AC/High
 - It is recommended first using AB/Low—switch position '1'.
2. Fasten the electrode holder to either terminal of the selected circuit and the ground cord to the other terminal.
 - Double electrode holders do not require a ground cord.
3. Clamp the work piece with the ground clamp to complete the circuit.
 - Not necessary with double electrode holders.
 - It also possible to clamp or bolt the ground cord to a vise to ground the work piece while holding it.
4. Turn selector switch (and/or change secondary circuit) to gradually increase heat until desired result is achieved for the application.
 - For best performance keep the inside of electrode tubes clean with steel brush (part #'s: 775 & 785).

To see our complete line of equipment:

- *Etching*
- *Soldering*
- *Demagnetizing*

Visit us at www.lumaelectricco.com

Parts checklist:

- (3) 5/16" Attachment Knob

Luma Electric Co.

3419 Silica Road
Sylvania, Ohio 43560

PH: 419-843-7842

FAX: 419-843-7984

email: info@lumaelectric.com

website: www.lumaelectricco.com