



Model: 631

Watts: 2500

Heat Stages: 18



Output Voltages

Switch Position	<u>AB/Low</u>	<u>BC/Med</u>	<u>AC/High</u>
1	1.9	2.8	4.7
2	2.1	3.1	5.2
3	2.2	3.4	5.7
4	2.5	3.7	6.2
5	2.7	4.0	6.7
6	2.9	4.3	7.2

1. Choose one of three secondary circuits: AB/Low, BC/Medium, AC/High
 - It is recommended first using AB/Low—switch position '1'.
2. Fasten the electrode holder to either terminal of the selected circuit and the ground cord to the other terminal.
 - Double electrode holders do not require a ground cord.
3. Clamp the work piece with the ground clamp to complete the circuit.
 - Not necessary with double electrode holders.
 - It also possible to clamp or bolt the ground cord to a vise to ground the work piece while holding it.
4. Turn selector switch (and/or change secondary circuit) to gradually increase heat until desired result is achieved for the application.
 - For best performance keep the inside of electrode tubes clean with steel brush (part #'s: 775 & 785).

To see our complete line of equipment:

- *Etching*
- *Soldering*
- *Demagnetizing*

Visit us at www.lumaelectricco.com

Parts checklist:

- ((3) 3/8" Attachment Knob
- (1) Switch Knob

Luma Electric Co.

3419 Silica Road
Sylvania, Ohio 43560
PH: 419-843-7842
FAX: 419-843-7984

email: info@lumaelectric.com
website: www.lumaelectricco.com